

GROUPS

 **Groups** [Add group](#) 

Group name	Description			Domain	
Accounts	Finance	1	2	<input type="radio"/>	
Design	Creative Group	1	3	<input type="radio"/>	
Documentation	Instructions	3	2	<input type="radio"/>	
Sales-Americas		2	2	<input type="radio"/>	
Sales-Europe		2	2	<input type="radio"/>	
Software	User Interface	2	3	<input type="radio"/>	

Assigning users to groups gives you powerful tools to manage large numbers of users and their privileges. Administrators can set access rights to entire groups rather than individually.

Important info: In text fields, you may enter 1 to 20 characters using letters, numbers, hyphen, and underscore. No other symbols, special characters, punctuation, or spaces may be used. Do not begin or end with a hyphen or underscore.

NEW GROUP

Choose **Add group** and fill out the required fields. Your LaCie NAS can have up to 256 groups.

New group ×

Group name

Description


DELETE A GROUP

To delete a group, choose the configuration icon (pencil), then select **Delete**. Confirm in the dialogue window. Deleting a group will not affect the data created by users in the group.

EXISTING GROUP

Group data is organized in a table.


- Choose the text in the **Group name** column to change the group name.
- Choose the empty space or text in the **Description** column to add or revise details for the group (optional).
- The number in the **Shares** column (connected dots icon) shows how many shares the group has access to. Choose the number to view the share(s).
- The number in the **Users** column (user icon) shows how many users belong to the group. Choose the number to view the user(s).
- A green light in the **Domain** column indicates that the group has been imported from a domain.
- Select the configuration icon (pencil) and choose:
 - **Users** to modify group members. In the resulting window, highlight a user, then choose the arrows to join/disjoin a user from the group.



- **Delete** to remove the group.

IMPORTING GROUPS FROM ACTIVE DIRECTORY

1. If you have successfully connected to an active directory domain (see [General Settings](#)), you will see a button labelled **Import from domain**. Choose the button.



2. A prompt allows you to search for groups on the domain. Begin by entering a the first letter of the group.

Import the group from the domain ✕

A ✕

Select items in the results list

- Account Operators
- Administrators
- Allowed RODC Password Replication Group
- Backup Operators
- Certificate Service DCOM Access
- Cryptographic Operators
- Denied RODC Password Replication Group
- DnsAdmins
- DnsUpdateProxy
- Domain Admins
- Domain Computers
- Domain Controllers
- Domain Guests
- Domain Users

1 / 5

Cancel Import

- To select multiple groups, hold down the Command key (Mac users) or Control key (Windows users).
- Choose the **Import** button.
- The imported groups will appear in the table with a green circle in the **Domain** column.

Groups Import from domain Add group ?

Group name	Description			Domain	
Accounts	Finance	0	4		
Design	Creative Group	0	4		
Documentation	Instructions	0	3		
Sales-Americas		0	5		
Sales-Europe		0	5		
Software	User Interface	0	5		
Account Operators	Members can administer domain user and group accounts	0			
Administrators	Administrators have complete and unrestricted access to th	0			
Backup Operators	Backup Operators can override security restrictions for the	0			
Cryptographic Operators	Members are authorized to perform cryptographic operator	0			

MANAGING GROUPS IMPORTED FROM AN ACTIVE DIRECTORY

Groups imported from an active directory are managed by the administrator of the original domain. However, the administrator of the LaCie NAS can delete an imported group from the device by selecting the configuration icon (pencil) and **Delete**.

Users and groups imported from an active directory may have their rights adjusted by the administrator of the original domain. See [Synchronize Users/Groups](#) for instructions on synchronizing changes from an active directory.